

## 调频接收机用 LT10.7M□ 系列陶瓷滤波器 LT10.7M□ Series of Ceramic Filter For FM Receiver

10.7MHz

### 技术特性 TECHNICAL CHARACTERISTICS

型号 Part Number	3分贝带宽 3dB Band Width (kHz)	20分贝带宽 20dB Band Width (kHz) max	插入损耗 Insertion Loss (dB) max	阻带衰减 Spurious Attenuation (9-12MHz)(dB)min
LT10.7MA5	280±50	650	6	30
LT10.7MS2	230±50	600	6	40
LT10.7MS3	180±40	520	7	40

输入/输出阻抗: 330Ω  
Input/Output Impedance: 330Ω

## 低损耗 LT10.7M□A10 系列陶瓷滤波器 LT10.7M□A10 Series of Ceramic Filter(Low-Loss Type)

10.7MHz

### 技术特性 TECHNICAL CHARACTERISTICS

型号 Part Number	3分贝带宽 3dB Band Width (kHz)	20分贝带宽 20dB Band Width (kHz) max	插入损耗 Insertion Loss (dB)	阻带衰减 Spurious Attenuation (9-12MHz)(dB)min
LT10.7MA5A10	280±50	590	2.5±2.0	30
LT10.7MS2A10	230±50	520	3.0±2.0	35
LT10.7MS3A10	180±40	470	3.5±1.5	35
LT10.7MJA10	150±40	360	4.5±2.0	35

输入/输出阻抗: 330Ω  
Input/Output Impedance: 330Ω

## 宽窄带型 LT10.7M□ 系列陶瓷滤波器 Wide/Narrow Band-width LT10.7M□ Series of Ceramic Filter

10.7MHz

### 技术特性 TECHNICAL CHARACTERISTICS

型号 Part Number	3分贝带宽 3dB Band Width (kHz)	20分贝带宽 20dB Band Width (kHz) max	插入损耗 Insertion Loss (dB)	阻带衰减 Spurious Attenuation (9-12MHz)(dB)min
LT10.7MA21	400min	950	3.0±2.0	20
LT10.7MA19	±175min	950	3.0±2.0	20
LT10.7MA20	330±50	680	4.0±2.0	30
LT10.7MHY	110±30	350	5.5±2.0	30
LT10.7MFP	20min	95	6.0max	24(10.7±1.0MHz)

输入/输出阻抗: 470Ω (A19), 330Ω (A21, A20, HY), 600Ω (FP)  
Input/Output Impedance: 470Ω (A19), 330Ω (A21, A20, HY), 600Ω (FP)