

**MODEL NO. RSE-6332D (One port power pass) 3-WAY SPLITTER**  
**RSE-6332A (All ports power pass)**

---

	Frequency Range(MHz)				
	5 ~ 47	47 ~ 1000	1000 ~ 1750	1750 ~ 2300	2300 ~ 2400
Insertion Loss (dB)	7.5	7.5	8.8	11.5	12.5
Isolation (dB)	16	20	20	20	18
Return Loss (dB)	10	12	12	11	11