



## Function..


- It is a multi-mode cell-phone disabler that can create a dome of about 5 to 10 meters in radius to shield you from been disturbed by cellular phone calls.
- It works on all cellular phone systems including GSM,PHS,CDMA,WCDMA,CDMA2000, or DECT.
- It is specially designed to be highly mobile that user can carry to any place conveniently.
- It can operate for more than 1.5 hours continuously per charge.

## Applications..

- Conference room, Class room, Church, Temple, Library, Restaurant, Publice office, Court room, Cinema, Concert hall etc. where disturbance free condition has to be maintained.
- ATM machine, Exam room, Trade center, Jail room etc. where cheat prevention has to be implemented.
- Home, Office, Car or Truck etc. where privacy needs to be maintained.
- Also suitable for disabling the popularizing auto-activation cell-phone devices used for bugging and peeping personal activities.
- It can be used for public safety applications. It is however not designed for hospital, gas-station environment or anti-mining application or small scale riot control.

## Characteristic Pic..

## Specification..



Mobile phone signal completely blocked



Intercept Bug Detector



Intercept Gaming Fraud

Frequency Coverage	GSM850/CDMA800:869-894MHz(Down Link) EGSM900:925-960MHz(Down Link) DCS1800:1805-1880MHz(Down Link) PCS1900:1930-1990MHz(Down Link) WCDMA/CDMA2000:2110-2170MHz(Down Link) PHS:1895-1919MHz DECT:1880-1900MHz
Transmission Power	GSM850/EGSM900/CDMA: $\geq 30$ dBm DCS1800/PCS1900/PHS: $\geq 27$ dBm WCDMA: $\geq 25$ dBm
Operative Range	Radius 8-10m(-50dBm down link signal strength)
Antenna	Dual miniature antenna
Battery	3.8V, 1700 mAh(single Li-battery)
Power Supply	50/60 AC 100-240(V) convert to DC 5V, 2A
Low Battery Indication	Yellow Power LED indicator dimming
LED Indication	Yellow:Power On; Red:Charging
Operation Mode	Mobile; Station
Dimension	23.5(T) x 60(W) x 96(L)mm(120mm with antenna)
Weight	101 grams(including battery)

## Complete set..

Cellular Phone Disabler X1	Battery X1	Charger X1